Serial Port Tools

Two main Unix tools for command line interfaces over serial ports are *cu* and *minicom*. I like the latter, my friend Dave likes the former. This article has tricks for using them.

cu

Misc info - cu utility bustage

cu can be sorta broken connecting to serial dev when cu installed without the uucp pkg. There needs to be a minimal /etc/uucp/port file in order for cu to be happy. Quick fix: create /etc/uucp/port as follows:

/etc/uucp/port

```
#
# Description for the TCP port - pretty trivial. DON'T DELETE.
#
port TCP
type tcp
```

- https://bugs.launchpad.net/ubuntu/+source/uucp/+bug/1094278
- https://bugs.launchpad.net/ubuntu/+source/uucp/+bug/584787

minicom

Minicom was originally designed for acoustic modems, and there are several things that are still in there.

Startup Commands

For one thing, it wants to *initialize* the modem by sending some strings to it when started up. Obviously, this is not good when using it for a connection to your network switch. The -o options stops that.

Additionally, I tend to use USB to Serial Port devices, so I have to explicitly tell minicom what port to use when I start up. Generally, this is /dev/ttyUSB0, and I use the -D parameter to set this.

My normal startup command is

```
minicom -o -D /dev/ttyUSB0
```

Menu Options

One of the reasons I like minicom is it is a clean, full screen interface. However, it has tons of options, all accessed as ^a-?, where ? is the specific option you want to execute. ^a-t brings up a menu of options.

From:
https://kb.unixservertech.com/ - **Unix Server Tech Knowledge Base**

Permanent link:
https://kb.unixservertech.com/software/serialtools

Last update: **2022/11/10 05:28**